
# **DIMENSIONS**

Project Name:



### **FEATURES**

Adjustable height electrogalvanized plated steel mounting ears with cutouts for various mounting methods. Standard bars (included) are innovative and incorporate rigid formed cross sections, joist positioning tabs, integral nails, auxiliary nailholes, T-Bar slots and holes for locking bars to T-Bar using #8 self-tapping screws (supplied by others). Bars extend 14"-24". Ears will also accept Caddy Bar #517B for fast installation in T-Bar ceilings, bars extend 27".

Heavy gauge electrogalvanized steel junction box, prewired and grounded. Listed for through branch circuit wiring. Thermal cutout

Extruded aluminum heat sink socket cup with Zinc plated steel hardware set screws for fast assembly. UL Listed medium base porcelain socket, with nickel plated brass screw shell.

Heavy gauge spun aluminum low iridescent reflector with self trimming white painted flange. Keyslots to secure reflector. Polished Flange

Aluminum frame with Integral Plaster Ring.

### REFLECTOR KIT

# OPEN

<u> </u>	
6″ Height	4" Aperture
<b>4000</b> Open	
Finish Options	71/2"   2711"
	/ /2   (/   \ )

Type:\_

SCL Specular Clear "Alzak" SGC Soft Glow Clear **ECL** Etch Clear WHT White Reflector

**Options** 

PF Polished Flange

#### **OPEN BAFFLED**

6" Height 4" Aperture

4050 Open Baffled

Finish Options

Specify reflector finish option - see above,

Black Baffle WH

then add baffle finish color White Baffle

#### **WALL WASH**


6" Height 4" Aperture

4001 Wall Wash Finish Options

SCL Specular Clear "Alzak"

**Options** 

PF Polished Flange



#### Features



Manufactured and Listed to UL 1598, ETL and CSA standards. Suitable for Damp Locations. Wet location under covered ceiling

# **ORDERING INFORMATION**

Lamps and Wattage	Housing	Reflector	Finish	Baffle	Options
100 A19 (MAX) 75 PAR16 39 PAR20	A4INC A4INC-GU24 PA4INC PA4INC-GU24	4000 Baffled 4050 Wall Wash	SCL SGC ECL WHT	BL WH	PF GSK 277V SD

4001

Options Descriptions

PF - Polished Flange GSK - Neoprene Foam Gasketing 277V SD - Step Down Transformer

Vantage reserves the right to change components, finishes or design details in any manner which does not alter the installed appearance or reduce performance and intended function.

▲ See Options pages for other options and finishes.

Suitable for use with LED lamps.

EXAMPLE: A4INC100-4000-SCL